

PowerMax™ CELLULAR COMBINERS



2-WAY | 4-WAY GLOBAL BAND CELLULAR COMBINERS

USE WITH ALL PowerMax™ CELLULAR BOOSTERS

NEW

Getting the most out of your cellular signal booster is easy when you have the right accessories to create a solution that is perfect for your specific application. Digital Antenna's new 2-way and 4-way global cellular combiners allow multiple cellular devices to be used simultaneously with direct-connect amplifiers and wireless repeater systems.

Visit our online Support Center at www.digitalantenna.com for customized installation solutions for PowerMax™ cellular boosters.



Two - 12' Dash-Mount Cables

DA-2384

DA-2384 2-Way Global Cell Combiner Kit Includes:

For easy ordering and installation, 2-way combiners are now available as a kit (# DA-2384) and include two 12' dash-mount adapter cables (C428-12) and a 2-way combiner (DA-2190).

- Two- 12' dash-mount cables (C428-12)
- 2-Way global Cell Combiner (DA-2190)



DA-2190

DA-2190 2-Way Global Cell Combiner



DA-4190

DA-4190 4-Way Global Cell Combiner

Specifications DA-2190 and DA-4190

Frequency	850 900 1800 1900 2100 MHz Bands (800-2200 MHz)
Impedance	50 ohm
Maximum Input Power	3 watts
Connectors	Mini-UHF female (50 ohm)
Insertion loss	DA-2190 = 3dB, DA-4190 = 6dB
Operating Temperature	-40 to +75° C -40 to 167° F
Dimensions	4" x 3.25"
Weight	DA-2190 = 5.8 oz, DA-4190 = 6.8 oz



Digital Antenna, Inc.
www.digitalantenna.com

5325 NW 108th Avenue
Sunrise, FL 33351

▶ t 954.747.7022
▶ f 954.747.7088